


Ajax Superior SpaceControl Jeweller

Wireless key fob with a panic button and control over security modes



This is a device of the Superior product line. Only accredited Ajax Systems partners can sell, install, and administer Superior products.

Ajax Superior SpaceControl Jeweller has a silicon overlay over the light indicators. This upgrade provides **improved protection against humidity**.

Arm

Arms the facility

Disarm

Disarms the facility

Night Mode


Activates Night Mode (switches devices to arming mode for perimeter security)

Panic

Notifies a security company and users of danger or emergency




Protection against accidental activation: double or long press




Jeweller communication technology

- Up to 1,300 m (4,250 ft) of radio communication in an open space
- Encryption and device authentication to prevent spoofing
- LED indication of button pressing



Flawless autonomy


- Up to 5 years of autonomous operation
- Pre-installed replaceable battery
- Notifications of low battery charge



Quick setup

- Pairing with a hub via QR code
- Remote control and configuration in the app
- It can be carried around in a pocket or on the key ring






<div>Compatibility with hubs and range extenders</div> <div></div> <div>For detailed information, scan the QR code or follow the link: ajax.systems/tools/devices-compatibility/?models=SC.S.J</div>	<div>Compliance with standards</div> <div>EN 50131 (Grade 2) PD 6662:2017 NFA2P SIA CP-01</div>	<div>Communication with a hub or range extender</div> <div>Jeweller communication technology</div> <div>Frequency bands 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the region of sales.</div> <div>Communication range up to 1,300 m up to 4,250 ft In an open space.</div>	<div>Power supply</div> <div>Battery 1 × CR2032 Pre-installed.</div> <div>Battery life up to 5 years</div>
<div>Installation</div> <div>Operating temperature range from –10 °C to +40 °C from 14 °F to 104 °F</div> <div>Operating humidity up to 95%</div> <div>Protection class IP32</div>	<div>Enclosure</div> <div>Color Black White</div> <div>Dimensions 65 × 37 × 10 mm 2.56" × 1.46" × 0.39"</div> <div>Weight 13 g 0.46 oz</div>	<div>Complete set</div> <div>Ajax Superior SpaceControl Jeweller 1 × CR2032 battery (pre-installed) Quick start guide</div>	



For detailed information, scan the QR code or follow the link:
ajax.systems/support/devices/ajax-superior-spacecontrol-jeweller



-  support@ajax.systems
-  [@AjaxSystemsSupport_Bot](https://t.me/AjaxSystemsSupport_Bot)
-  ajax.systems